

Pure post-stage broadcast amplifier(800W) FP4-G8800S



Feature:

1. Adopt advanced and efficient power amplifier circuit, strong power output, super load capacity, equipped with 1 audio input, the volume can be adjusted independently
2. The equipment is equipped with abnormal working protection warning function. When the input signal is too large, the load is too heavy, the temperature is too high, and the line circuit is in trouble, the corresponding indicator light prompts, which has extremely high reliability
3. Adopt aluminum alloy panel design, beautiful and practical

Specification:

Rated output power	800W
Input sensitivity	0dBV
Signal-to-noise ratio	>80dB
Damping coefficient	200:1
Common mode suppression	greater than 90dB
Frequency response	50Hz-15kHz (± 3 dB)
Total harmonic distortion	4W/1kHz <0.3%
Rise rate	>15V/microsecond
Indicator lights	"power", "clipping", "signal", "protection" and "overtemperature"