



Feature:

1. Waistpack wireless transmitter, can be paired with a clip microphone or a headset microphone
2. High contrast display: can display frequency, frequency number, group number, battery power, transmission signal strength, mute status and other information
3. Standard mini XLR interface, strong compatibility, can be connected to different microphones
4. Equipped with 4 setting buttons, equipped with an easy-to-use navigation menu, easy to set up and use
5. Transmitter parameters can be modified: support modification of frequency, transmission power, volume, etc. on the microphone
6. Support multi-color LED indicator: can display 8 different color labels to identify paired channels

Specification:

Audio interface	Mini-XLR
Frequency range	660.05-685.05MHz
Dynamic range	101dB
Frequency response	60-18KHz
Frequency stability	±0.005%
Working distance	150m (open and interference-free)
Battery specifications	2×1.5V AA
Output power	high/medium/low three-speed switchable
Weight	75g (excluding battery and microphone)
Shell material	ABS
Dimensions	66*23*88 mm (length*width*height, excluding antenna)
Battery life	high power about 7 hours; Medium power about 8 hours; Low power about 10 hours
Lavalier microphone parameters	
Directional characteristics	single direction
Frequency response	50Hz-20KHz
Sensitivity	-23±3dB
Output impedance	≤ 2.2KΩ
Signal-to-noise ratio	≥66dB
Connection	wired (1 meter)
Interface	Mini XLR
Color	black