

Smart Broadcast Host FP4-C6801



• Feature:

- 1. Adopt 3-inch TFTRGB true color display screen, clear image, vivid color
- 2. Adopt industrial resistive touch screen, reliable performance, simple operation
- 3. Support automatic screen lock function, save energy, and extend screen life

4. Support lossless and various decoding formats: MP3, MP2, MP1, WMA, APE, FLAC, AC3, DTS, RA, AAC, AMR, ATRC, WAV

- 5. Support large-capacity TF card and USB flash drive
- 6. Support automatic music sorting function, no special numbering software is required
- 7. Support ten sets of timetable programs, each set can program 999 timers
- 8. Each timer can be specified to play, loop play, random play, etc
- 9. Support computer editing timer program
- 10. Built-in FM radio function, convenient for listening to radio programs

11. Intelligent voice recognition technology, microphone excitation to turn on the power of the amplifier sensitively and quickly

- 12. Super load capacity, each power socket can load 1000W amplifier
- 13. The power sockets can be controlled separately, supporting 6+1 partitions
- 14. Support output power sequencer short-circuit signal function
- 15. Support short-circuit alarm signal input function
- 16. Support line input switch function

Specification:

Music storage	SD card\U disk
U disk file system	FAT (FAT16), FAT32
Support SD card\U disk capacity	128MB-32GB
Support playback file formats	MP3, MP2, MP1, WMA, APE, FLAC, AC3, DTS, PA, AAC, AMR, ATRC, WAV
Signal-to-noise ratio	>90dB
Total harmonic distortion	<0.1%
Power supply voltage	AC220V±10%
Power consumption	standby <5W, full load <10W
Amplifier control power	single channel <1000W
Peripheral control power	single channel <300W
Partition control power	single channel <300W