

Smart broadcast host FP4-C6871



Feature:

- 1. 3-inch TFT RGB true-color display for crisp images and vivid colors
- 2. Industrial resistive touchscreen for reliable performance and simple operation
- 3. Automatic screen lock, saving energy and extending screen life
- 4. Supports lossless and various decoding formats: MP3, MP2, MP1, WMA, APE, FLAC, AC3, DTS, RA, AAC, AMR, ATRC, WAV
- 5. Supports large-capacity TF cards and USB flash drives
- 6. Automatic music sorting, eliminating the need for dedicated scheduling software
- 7. Supports ten schedule programs, each with 999 entries
- 8. Each schedule can be assigned to play, loop, or shuffle play
- 9. Supports computer-controlled schedule editing
- 10. Built-in FM radio for convenient radio listening
- 11. Intelligent voice recognition technology allows for quick and sensitive power-on of the amplifier via microphone activation
- 12. High power load capacity: Each power outlet can handle a 1000W amplifier
- 13. Power outlets can be individually controlled, supporting 6+1 partitions
- 14. Supports output power sequencer short-circuit signal function
- 15. Supports short-circuit alarm signal input function
- 16. Supports line input switch function

Specification:

Music storage	SD card/USB flash drive
USB flash drive file system	FAT (FAT16), FAT32
128MB-32GB	Supported SD card/USB flash drive capacity
Supported playback file formats	MP3, MP2, MP1, WMA, APE, FLAC, AC3, DTS, PA, AAC, AMR, ATRC, WAV
Signal-to-Noise Ratio	>90dB
Total Harmonic Distortion	<0.1%
Power Supply Voltage	AC220V ±10%
Power Consumption	Standby <5W, Full Load <10W
Amplifier Control Power	Single Channel <1000W
Peripheral Control Power	Single Channel <300W
Zone Control Power	Single Channel <300W

