



► Specification:

Item	Specification
DMX512 Channels	1024
Max Number of Intelligent Fixtures	96
Fixture Address Reassignment	Supported
Fixture Pan/Tilt Swap	Supported
Fixture Channel Inversion	Supported
Fixture Channel Slope Mode Switching	Supported
Max Control Channels per Fixture	40 main channels + 40 fine channels
Fixture Library	Supports Pearl R20 fixture library
Number of Storable Scenes	60
Number of Simultaneous Scenes	10
Total Steps in Multi-Step Scenes	600
Scene Time Control	Fade In, Fade Out, LTP Slope
Graphics per Scene	Up to 5
Scene Activation and Dimming via Fader	Supported
Scene Interlock	Supported
Scene Trigger by Button	Supported
Built-in Shape Generator	Supports Dimmer, Pan/Tilt, RGB, CMY, Color, Gobo, Iris, and Focus effects
Simultaneous Running Shapes	5
Master Fader	Supported
Global Blackout / Replay / Instant Blackout	Supported
Channel Value Adjustment via Jog Wheel	Supported
Channel Value Adjustment via Fader	Supported
Fader Dimming	Supported
USB Support	FAT32 format
Dimensions	480 × 420 × 130 mm